marantz



With a slim profile that doesn't sacrifice performance for looks, the Marantz NR1609 7.2 channel AV receiver supports immersive, object-based audio and the latest HDMI specifications. Enjoy movies with three-dimensional audio through Dolby Atmos, DTS:X and DTS Virtual:X, and watch your favorite movies and shows in 4K 60Hz video, 4:4:4 Pure Color sub-sampling, BT.2020, HDR and Dolby Vision. Enjoy your favourite music services via Bluetooth, Apple AirPlay or the HEOS app. Control NR1609 with your voice and Amazon Alexa — download the HEOS Home Entertainment skill and ask Alexa to play, pause or stop music, switch inputs for your different media players, turn up the volume and more.

Highlights	Your Benefits
Slim Design 7.2 channel AV Receiver with 90W per channel	Enough power to fill your living room with renowned Marantz sound
Dolby Atmos (up to 5.1.2), DTS:X and DTS:Virtual X	Immersive 3D sound with effects from overhead
AirPlay, Bluetooth, Internet Radio, Spotify Connect, Network Audio Streaming	Access to almost unlimited online music sources
Works with Amazon Alexa via the HEOS Home Entertainment skill	Enjoy hands-free control with Amazon Alexa and your voice (differs per country)
Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth	Improved network stability especially in WiFi-crowded homes
4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log Gamma	Latest HDMI standard for future-proof compatibility
8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support	Plenty of inputs for your Blu-ray Player, game console and more
DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High Resolution audio streaming, even gapless
Audyssey MultEQ, Dynamic Volume and Dynamic EQ	Delivering perfect equalization for your individual room
Integrated Phono input to directly connect your turntable	Enjoy the pure intent of each recording within your vinyl collection
Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App	Hassle-free installation, setup and operation
Intelligent ECO mode with off/on/auto setting	Energy-conscious without compromising on performance







































marantz

NR1609

ULTRA-SLIM 7.2 CHANNEL AV RECEIVER WITH 3D AUDIO AND ONLINE MUSIC STREAMING





FEATURES	NR1609				
MULTICHANNEL SURROUND					
DTS HD Master / DTS:X / DTS Neural:X / DTS:Virtual X	• / • / • / •				
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •				
Multichannel Stereo	•				
Compressed audio Enhancer: MDAX2	•				
Audyssey	MultEQ				
Audyssey Dynamic EQ / Dynamic Volume	• / •				
Audyssey MultEQ Editor App support	•				
NETWORK / SOURCES					
Network Audio Streaming	•				
HEOS Multiroom integrated	•				
Voice Control	Works with Amazon Alexa*				
Lossy formats MP3 / WMA / AAC	• / • / •				
Lossless formats FLAC / ALAC / WAV	• / • / •				
DSD Streaming	• (2.8 MHz / 5.6 MHz)				
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •				
Gapless playback	• (FLAC, WAV, ALAC, DSD)				
AirPlay audio streaming	•				
Internet Radio (TuneIn)	•				
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •				
Compatible with Remote APP for Smart Phones	Android/iOS				
Ethernet / Wi-Fi	• / • (dual antenna / dual band)				
Network: (IP-control / update)	• / •				
Front Inputs: HDMI / USB	• / •				
USB Audio	•				
FM / AM Tuner	• / •				
Bluetooth	•				
HDMI					
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •				
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •				
HDMI pass through on stand-by	•				
3D video pass through	•				
Videoprocessing and -scaling	1080p, 4K 30/25/24Hz				
* This feature is not available in all countries					

*	This feature	is	not	available	in	all	countries.

INPUT	rs/outputs							
VIDEO								
Compo	site In / Out		3 / 1					
Compo	nent In / Out		2 / 1					
HDMI	In / Out		7+1 / 1					
AUDIO								
Analog	jue In / Out	3 / 0						
Phono	ln	1						
Digital	Optical In	1						
Digital	Coaxial In	1						
Multic	hannel Pre Out	• (2.2)						
Zone a	udio preout	•						
Subwo	ofer Out	2						
SPECIFICATIONS								
Numbe	er of poweramps		7					
Power	Output per channel							
6 ohm,	1 kHz, 1%, 1ch Drive	90 W						
6 ohm,	1 kHz. 0.7%, 2ch Driv	е	70 W					
8 ohm,	20 Hz - 20 kHz, 0.08%	, 2ch Drive	50 W					
Audio	Signal to Noise Ratio		98 dB					
GENE	RAL							
Availal	ole colours: Black / Sil	• / •						
Systen	n Remote Control	RC035SR						
Power	Consumption in W	250						
Power	Consumption No-Sour	30 / 40						
Standb	y Consumption in W	0.1 (with CEC 0.5)						
Maxim	um Dimensions (W x I	x H) in mm	440 x 376 x 105					
Weigh	t in kg		8.3					
EAN								
EU	NR1609/N1B	4951035065228	Black					
	NR1609/N1SG	4951035065235	Silver-Gold					
UK	NR1609/T1B	4951035066485	Black					
	NR1609/T1SG	4951035066492	Silver-Gold					

A Division of Sound United Beemdstraat 11 5653 MA Eindhoven The Netherlands The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTSX, and the DTSX logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

D&M Furone B.V

^{*} All specs can be subject to change.